



Auswahltabelle Bremswiderstände PI500

	Spannung	Leistung	Empfohlener Bremswiderstand
PI500	1x230V	0,75kW	200 Ohm/120W
		1,5kW	100 Ohm/300W
		2,2kW	70 Ohm/300W
		4kW	40 Ohm/500W
	3x400V	0,75kW	750 Ohm/120W
		1,5kW	400 Ohm/300W
		2,2kW	250 Ohm/300W
		4kW	150 Ohm/500W
		5,5kW	100 Ohm/500W
		7,5kW	75 Ohm/780W
		11kW	50 Ohm/1000W
		15kW	40 Ohm/1500W
		18,5kW	32Ω/4800W
		22kW	27.2Ω/4800W
		30kW	20Ω/6000W
		37kW	16Ω/9600W
		45kW	13.6Ω/9600W
		55kW	10Ω/12000W
		75kW	6.8Ω/12000W
		93kW	6.8Ω/12000W
		110kW	6.8Ω/12000W
		132kW	6.8Ω/12000W
		160kW	6.8Ω/12000W
		187kW	6.8Ω/12000W
200kW	6.8Ω/12000W		
220kW	6.8Ω/12000W		
250kW	6.8Ω/12000W		